

MANUAL DO USUÁRIO

JKL-1803PX

RIBALTA PIXEL IP65



Por favor, leia o Manual do Usuário antes de utilizar o produto e guarde-o para futuras pesquisas.

ATENÇÃO: Por favor leia o manual do usuário cuidadosamente, ele contém informações importantes sobre instalação, operação e manutenção

INFORMAÇÕES TÉCNICAS:

Voltagem: AC100V~256V/50~60Hz

Consumo: 70w

LED: 18pcs LEDS RGB 3IN1 TRILED

Pixel Mapping: Controle individual para cada LED e Cor

Mistura de Cores: R-G-B- diferentes saídas de cores, mistura e troca de cores variadas, 16 Milhões de cores.

Ângulo de abertura: 25°

Vida útil do LED: 50.000.00 (estimado)

Modos de Trabalho: DMX512/AUTOMATICO/MASTER-SLAVE

DMX: 8CH ou 72CH

Dimmer: Dimmer Linear 0/100%

Strobo: Estrobo Ajustável, velocidade variável

Display: Display Digital

Conexão Master/Slave: Pode ser conectada até 24 unidades simultaneamente

Sistema de proteção: IP65 (resistente a água)

Temperatura de Trabalho: -18~40°C

Carcaça: Alumínio

Tamanho: 100cm x 7,6cm x 10cm

Peso: 3.5kg

CONFIGURAÇÃO DMX 512:

Modo de operação: 2 Canais

Canal	Valor DMX	Função
CH1	000-005	Null
	006-016	Red
	017-027	Green
	028-038	Blue
	039-049	Yellow
	050-060	Pink
	061-071	Cyan
	072-082	White
	083-093	Jump effect 01
	094-104	Jump effect 02
	105-115	Jump effect 03
	116-126	Jump effect 04
	127-137	Jump effect 05
	138-148	Jump effect 06

	149-159	Jump effect 07
	160-170	Jump effect 08
	171-181	Loops jump effect 01 to 08
	182-192	Red shade effect
	193-203	Green shade effect
	204-214	Blue shade effect
	215-225	Pink shade effect
	226-236	Yellow shade effect
	237-247	Loops red to yellow shade effect
	248-255	Sound active
	CH2	000-255

Modo de operação: 3 Canais

Canal	Valor DMX	Função
CH1	000-255	Red Dimming, From dark to light
CH2	000-255	Green Dimming, From dark to light
CH3	000-255	Blue Dimming, From dark to light

Modo de operação: 4 Canais

Canal	Valor DMX	Função
CH1	000-255	RGB Total Dimming, From dark to light
CH2	000-255	Red Dimming, From dark to light
CH3	000-255	Green Dimming, From dark to light
CH4	000-255	Blue Dimming, From dark to light

Modo de operação: 5 Canais

Canal	Valor DMX	Função
CH1	000-255	1-8# Red Dimming, From dark to light
CH2	000-255	1-8# Green Dimming, From dark to
CH3	000-255	1-8# Blue Dimming, From dark to light
CH4	000-255	9-18# Red Dimming, From dark to light
CH5	000-255	9-18# Green Dimming, From dark to
CH6	000-255	9-18# Blue Dimming, From dark to light

Modo de operação: 8 Canais

Canal	Valor DMX	Função
CH1	000-255	RGB Total Dimming, From dark to
CH2	007-255	RGB Strobe, Speed from slow to fast
CH3	000-005	Null

	016-025	
	026-035	
	036-045	
	056-065	
	066-075	
	076-085	
	086-095	
	096-105	
	106-115	
	116-125	
	126-135	
	136-145	Jump effect 01
	146-155	Jump effect 02
	156-165	Jump effect 03
	166-175	Jump effect 04
	176-185	Jump effect 05
	186-195	Jump effect 06
	196-205	Jump effect 07
	206-215	Jump effect 08
	216-225	Loops jump effect 01 to 08

	226-235	Yellow shade effect
	236-245	Loops red to yellow shade effect
	246-255	Sound active
CH4	000-255	Effects Speed from slow to fast
CH5	000-255	When run customize effect 1#-13#,choose backdrops color.
CH6	000-255	Red Dimming, From dark to light
CH7	000-255	Green Dimming, From dark to light
CH8	000-255	Blue Dimming, From dark to light

Modo de operação: 9 Canais

Canal	Valor DMX	Função
CH1	000-255	1-6# Red Dimming, From dark to light
CH2	000-255	1-6# Green Dimming, From dark to
CH3	000-255	1-6# Blue Dimming, From dark to light
CH4	000-255	7-12# Red Dimming, From dark to light
CH5	000-255	7-12# Green Dimming, From dark to
CH6	000-255	7-12# Blue Dimming, From dark to light
CH7	000-255	13-18# Red Dimming, From dark to
CH8	000-255	13-18# Green Dimming, From dark to
CH9	000-255	13-18# Blue Dimming, From dark to

Modo de operação: 18 Canais

Canal	Valor DMX	Função
CH1	000-255	1-3# Red Dimming, From dark to light
CH2	000-255	1-3# Green Dimming, From dark to
CH3	000-255	1-3# Blue Dimming, From dark to light
CH4	000-255	4-6# Red Dimming, From dark to light
CH5	000-255	4-6# Green Dimming, From dark to
CH6	000-255	4-6# Blue Dimming, From dark to light
CH7	000-255	7-9# Red Dimming, From dark to light
CH8	000-255	7-9# Green Dimming, From dark to
CH9	000-255	7-9# Blue Dimming, From dark to light
CH10	000-255	10-12# Red Dimming, From dark to
CH11	000-255	10-12# Green Dimming, From dark to
CH12	000-255	10-12# Blue Dimming, From dark to
CH13	000-255	13-15# Red Dimming, From dark to
CH14	000-255	13-15# Green Dimming, From dark to
CH15	000-255	13-15# Blue Dimming, From dark to
CH16	000-255	16-18# Red Dimming, From dark to
CH17	000-255	16-18# Green Dimming, From dark to
CH18	000-255	16-18# Blue Dimming, From dark to

Modo de operação: 54 Canais

Canal	Valor DMX	Função
CH1	000-255	1# Red Dimming, From dark to light
CH2	000-255	1# Green Dimming, From dark to light
CH3	000-255	1# Blue Dimming, From dark to light
CH4	000-255	2# Red Dimming, From dark to light
CH5	000-255	2# Green Dimming, From dark to light
CH6	000-255	2# Blue Dimming, From dark to light
CH7	000-255	3# Red Dimming, From dark to light

CH8	000-255	3# Green Dimming, From dark to light
CH9	000-255	3# Blue Dimming, From dark to light
CH10	000-255	4# Red Dimming, From dark to light
CH11	000-255	4# Green Dimming, From dark to light
CH12	000-255	4# Blue Dimming, From dark to light
CH13	000-255	5# Red Dimming, From dark to light
CH14	000-255	5# Green Dimming, From dark to light
CH15	000-255	5# Blue Dimming, From dark to light
CH16	000-255	6# Red Dimming, From dark to light

CH17	000-255	6# Green Dimming, From dark to light
CH18	000-255	6# Blue Dimming, From dark to light
CH19	000-255	7# Red Dimming, From dark to light
CH20	000-255	7# Green Dimming, From dark to light
CH21	000-255	7# Blue Dimming, From dark to light
CH22	000-255	8# Red Dimming, From dark to light
CH23	000-255	8# Green Dimming, From dark to light
CH24	000-255	8# Blue Dimming, From dark to light
CH25	000-255	9# Red Dimming, From dark to light
CH26	000-255	9# Green Dimming, From dark to light
CH27	000-255	9# Blue Dimming, From dark to light
CH28	000-255	10# Red Dimming, From dark to light
CH29	000-255	10# Green Dimming, From dark to light
CH30	000-255	10# Blue Dimming, From dark to light
CH31	000-255	11# Red Dimming, From dark to light
CH32	000-255	11# Green Dimming, From dark to light
CH33	000-255	11# Blue Dimming, From dark to light
CH34	000-255	12# Red Dimming, From dark to light
CH35	000-255	12# Green Dimming, From dark to light
CH36	000-255	12# Blue Dimming, From dark to light
CH37	000-255	13# Red Dimming, From dark to light
CH38	000-255	13# Green Dimming, From dark to light
CH39	000-255	13# Blue Dimming, From dark to light
CH40	000-255	14# Red Dimming, From dark to light
CH41	000-255	14# Green Dimming, From dark to light
CH42	000-255	14# Blue Dimming, From dark to light
CH43	000-255	15# Red Dimming, From dark to light
CH44	000-255	15# Green Dimming, From dark to light
CH45	000-255	15# Blue Dimming, From dark to light
CH46	000-255	16# Red Dimming, From dark to light
CH47	000-255	16# Green Dimming, From dark to light
CH48	000-255	16# Blue Dimming, From dark to light
CH49	000-255	17# Red Dimming, From dark to light
CH50	000-255	17# Green Dimming, From dark to light
CH51	000-255	17# Blue Dimming, From dark to light
CH52	000-255	18# Red Dimming, From dark to light
CH53	000-255	18# Green Dimming, From dark to light
CH54	000-255	18# Blue Dimming, From dark to light

Modo de operação: 56 Canais

Canal	Valor DMX	Função
CH1	000-255	RGB Total Dimming, From dark to light
CH2	007-255	RGB Strobe,SPEED FROM SLOW TO
CH3	000-255	1# Red Dimming, From dark to light
CH4	000-255	1# Green Dimming, From dark to light
CH5	000-255	1# Blue Dimming, From dark to light
CH6	000-255	2# Red Dimming, From dark to light
CH7	000-255	2# Green Dimming, From dark to light
CH8	000-255	2# Blue Dimming, From dark to light
CH9	000-255	3# Red Dimming, From dark to light
CH10	000-255	3# Green Dimming, From dark to light
CH11	000-255	3# Blue Dimming, From dark to light
CH12	000-255	4# Red Dimming, From dark to light
CH13	000-255	4# Green Dimming, From dark to light
CH14	000-255	4# Blue Dimming, From dark to light
CH15	000-255	5# Red Dimming, From dark to light
CH16	000-255	5# Green Dimming, From dark to light
CH17	000-255	5# Blue Dimming, From dark to light
CH18	000-255	6# Red Dimming, From dark to light
CH19	000-255	6# Green Dimming, From dark to light
CH20	000-255	6# Blue Dimming, From dark to light
CH21	000-255	7# Red Dimming, From dark to light
CH22	000-255	7# Green Dimming, From dark to light
CH23	000-255	7# Blue Dimming, From dark to light
CH24	000-255	8# Red Dimming, From dark to light
CH25	000-255	8# Green Dimming, From dark to light
CH26	000-255	8# Blue Dimming, From dark to light
CH27	000-255	9# Red Dimming, From dark to light
CH28	000-255	9# Green Dimming, From dark to light
CH29	000-255	9# Blue Dimming, From dark to light
CH30	000-255	10# Red Dimming, From dark to light
CH31	000-255	10# Green Dimming, From dark to light
CH32	000-255	10# Blue Dimming, From dark to light
CH33	000-255	11# Red Dimming, From dark to light
CH34	000-255	11# Green Dimming, From dark to light
CH35	000-255	11# Blue Dimming, From dark to light
CH36	000-255	12# Red Dimming, From dark to light
CH37	000-255	12# Green Dimming, From dark to light
CH38	000-255	12# Blue Dimming, From dark to light
CH39	000-255	13# Red Dimming, From dark to light

CH40	000-255	13# Green Dimming, From dark to light
CH41	000-255	13# Blue Dimming, From dark to light
CH42	000-255	14# Red Dimming, From dark to light
CH43	000-255	14# Green Dimming, From dark to light
CH44	000-255	14# Blue Dimming, From dark to light
CH45	000-255	15# Red Dimming, From dark to light
CH46	000-255	15# Green Dimming, From dark to light
CH47	000-255	15# Blue Dimming, From dark to light
CH48	000-255	16# Red Dimming, From dark to light
CH49	000-255	16# Green Dimming, From dark to light
CH50	000-255	16# Blue Dimming, From dark to light
CH51	000-255	17# Red Dimming, From dark to light
CH52	000-255	17# Green Dimming, From dark to light
CH53	000-255	17# Blue Dimming, From dark to light

CH54	000-255	18# Red Dimming, From dark to light
CH55	000-255	18# Green Dimming, From dark to light
CH56	000-255	18# Blue Dimming, From dark to light

KEY AND DISPLAY FUNCTIONS

1. Intruções das teclas.



MENU : Página 1 funções, loops e adicionar ;

UP : funções, valores e adicionar ;

DOWN : funções, valores e diminuir ;

ENTER : Salvar ajustes ;

2. Instruções de Display;

No.	Visor	Valor	Função
1	d001	001- 512	DMX512 Address ,2 Channels mode
2	ID01	ID01-ID54	Convenient 54 Channels mode DMX512 Address set : ID1: dmx512 address is 001(54 Channels mode); ID2: dmx512 address is 055(54 Channels mode);
3	R255	000 - 255	Red Dimming, From dark to light
4	G255	000 - 255	Green Dimming, From dark to light

5	B255	000 - 255	Blue Dimming, From dark to light
6	FF99	00 - 99	RGB Strobe,Speed from slow to fast
7	1J00	0 - 20	Jump effect 01,Speed from slow to fast
8	2J00	0 - 20	Jump effect 02,Speed from slow to fast
9	3J00	0 - 20	Jump effect 03,Speed from slow to fast
10	4J00	0 - 20	Jump effect 04,Speed from slow to fast
11	5J00	0 - 20	Jump effect 05,Speed from slow to fast
12	6J00	0 - 20	Jump effect 06,Speed from slow to fast
13	7J00	0 - 20	Jump effect 07,Speed from slow to fast
14	8J00	0 - 20	Jump effect 08,Speed from slow to fast
15	9J00	0 -20	Loops jump effect 01 to 08
16	1d00	0 -20	Red shade effect,Speed from slow to fast
17	2d00	0 -20	Green shade effect,Speed from slow to fast
18	3d00	0 -20	Blue shade effect,Speed from slow to fast
19	4d00	0 -20	Pink shade effect,Speed from slow to fast
20	5d00	0 -20	Yellow shade effect,Speed from slow to fast
21	6d00	0 -20	Loops red to yellow shade effect ,Speed from slow to fast
22	Sud0	0 - 9	Sound active,Speed from slow to fast
23	CH02	02/03/04/06/ 08/09/18/54/ 56	DMX channel mode set

TERMO DE GARANTIA

Este produto foi cuidadosamente avaliado em todas as fases do seu processo de fabricação. Entretanto, na improvável ocorrência de alguma falha, A Led Light Indústria e Comércio Importação e Exportação assegura ao comprador original deste produto garantia contra qualquer defeito de material ou de fabricação no período de 90 DIAS a partir da data de aquisição, apresentando nota fiscal de compra, número de serial do produto e carimbo da loja datado neste Manual. A garantia cobre eventuais defeitos no material empregado ou na fabricação.

Condições de Garantia: a garantia perde sua validade se:

- O solicitante da garantia não for o comprador original, não estando a compra comprovada por nota fiscal para todos os fins legais.
- O número de série do produto esteja raspado ou tenha sido retirado.
- Alguma parte, peça ou componente do produto estiver violado.
- Lacre da JK LIGHT
- Cobertura da Garantia: a JK LIGHT dá cobertura a todas as partes, peças ou componentes que apresentem falha de fabricação dentro do prazo de garantia.

A JK LIGHT não dá cobertura às despesas:

- Geradas no conserto do produto danificado por mau acondicionamento pelo comprador para o transporte.
- Manutenção periódica e reparação ou peças devido ao desgaste normal do produto.
- Decorrentes do transporte do produto em garantia na cidade onde exista Assistência Técnica autorizada.
- Oriunda do produto que contenha adulteração ou rasuras no número de série.
- Decorrentes da fadiga esperada na utilização normal do produto.
- Com acidentes, embalagens, seguros de qualquer natureza, inclusive no transporte, e decorrentes do uso indevido do produto ou sem a devida observação às recomendações técnicas da JK LIGHT.

Nenhum valor será devido ao comprador pelo período em que o seu equipamento permanecer inoperante, nem, tampouco, o comprador poderá pedir/reclamar compensação ou indenização, por despesas diretas ou indiretas, decorrentes da reparação ou substituição do produto.

Caso fique impossibilitado o uso do produto, dentro do prazo de garantia, em razão de defeito de fabricação, e, não existindo mais peças para reposição, a JK LIGHT poderá substituir o produto por um modelo similar, sem bônus para o cliente.

A JK LIGHT não se responsabiliza e não cobre qualquer custo ou indenização decorrente de eventual falha do equipamento que resulte em danos ao usuário a não ser o conserto ou a reposição do próprio equipamento por ela produzido.



(48) 3028 7778

contato@ledlaserlight.com.br

www.ledlaserlight.com.br

